

Features

- Ultra Slim design , the height is just 20mm
- With LED display show three digital true voltage , more accurate and safe for notebook
- Output up to 100W
- Compatible with most of notebook brands, such as : Acer, ASUS, Compaq, Delta, HP, Fujitsu, Gateway, Toshiba, Liteon, NEC, BenQ, Sony, Lenovo etc
- Less than 0.5W in standby , low ripple and low interference
- Automatic voltage regulation in the connectors, which preventing any wrong voltage setting damage.
- Warranty: 2 years.

Specification

- Input AC: AC 100 to 240V 50/60Hz
- Output DC: 15V /16V /18.5V/ 19V /19.5V@5A max
- Output power max.: 100W
- Efficiency:> 80%
- Standby consumption: <0.5 watts
- Number of tips: 8
- Net weight: About 450g
- Short-circuit protection: YES
- Over-current protection: YES
- Over-voltage protection: YES
- Dimensions (LxWxH): 150 x 65 x 20 mm
- Low Ripple: <100mv
- Operating temperature: 0°C ~40°C
- Operating humidity : 20%~85% RH.

8 Tips Spec.

Type:	output	connector size	Fit for notebook
M1	15V	6.3*3.0mm	Toshiba
M2	16V	5.5*2.5mm	IBM, Lenovo
M3	16V	6.5*4.4mm (with 1.4mm pin)	Sony,Fujitsu
M4	18.5V	4.8*1.7mm	Compaq, HP,LG
M5	19V	5.5*2.5mm	Acer,ASUS, Compaq, Delta,HP, Fujitsu,Gateway,Toshiba,Liteon,NEC,,BenQ,
M6	19V	5.0*3.0mm (with 1.0mm pin)	Samsung
M7	19V	5.5*2.1mm	Acer,ASUS, Compaq, Delta,HP, Fujitsu,Gateway,Toshiba,Liteon,BenQ,
M8	19.5V	6.5*4.4mm(with 1.4mm pin)	Sony
oneUSB 5V/1A	MP3/MP4 mobile phone and other digital products		